9422CMP10

Circuit breaker accessory, PowerPacT M/P, disconnect mechanism, cable operated, 120in cable



| Main | |
|---------|----------------------------------|
| Range | 9422C |
| Product | Single Cable Operating Mechanism |

Complementary

| Circuit Breaker Type | PowerPact M or P 3 | |
|----------------------|--------------------|--|
| Included | Ordered separately | |
| Number of Cables | 1 | |
| Cable Length | 120 in | |

Ordering and shipping details

| Category | 21732-9422 | |
|-------------------|--------------|--|
| Discount Schedule | CP1 | |
| GTIN | 785901958642 | |
| Returnability | No | |
| Country of origin | MX | |

Packing Units

| Unit Type of Package 1 | PCE |
|------------------------------|-------------------------|
| Number of Units in Package 1 | 1 |
| Package 1 Weight | 16.00 lb(US) (7.258 kg) |

Offer Sustainability

| California proposition 65 | WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov | |
|----------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--|
| REACh Regulation | REACh Declaration | |
| REACh free of SVHC | Yes | |
| EU RoHS Directive | Compliant EEU RoHS Declaration | |
| Toxic heavy metal free | Yes | |
| Mercury free | Yes | |
| China RoHS Regulation | [™] China RoHS Declaration | |
| RoHS exemption information | €Yes | |
| PVC free | Yes | |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or intelability of these products for specific user applications. It is the douty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Warranty 18 months